

# Wavelets with compact support

## 1. Introduction

In this chapter we study wavelets with compact support. It is quite easy to see that if the father wavelet or scaling function  $\varphi$  has compact support, then the filter  $\alpha$  has compact support as well, i.e., it is a finite sequence. At least in the case where  $\varphi$  decays sufficiently rapidly at  $\pm\infty$  the converse also holds.

First we consider some results that are somewhat more general than what we actually need for the analysis of wavelets.

## 2. Dilation equations

In Chapter 4 we found that a crucial property of the father wavelet or scaling function  $\varphi$  determining a multiresolution is that it satisfies the dilation equation

$$(5.1) \quad \varphi = 2 \sum_{k \in \mathbb{Z}} \alpha(k) \varphi(2 \bullet - k).$$

In this section we look at some properties of a generalization of this equation.

First we observe that every sequence  $(\alpha(k))_{k \in \mathbb{Z}}$  can be identified with a Radon measure, i.e. a local measure, by defining  $\alpha_\diamond(E) = \sum_{k \in E} \alpha(k)$  for every bounded set  $E \in \mathbb{R}$ . If we assume that  $\alpha \in l^1(\mathbb{Z})$ , then  $\alpha_\diamond$  is a finite measure. Now (5.1) can be rewritten as

$$\varphi = 2(\alpha_\diamond * \varphi)(2 \bullet)$$

where  $*$  denotes convolution. Thus the generalized equation that we will be looking at here is

$$(5.2) \quad f = \rho(\mu * f)(\rho \bullet),$$

where  $\rho$  is some real number  $> 1$  and  $\mu \in M(\mathbb{R}; \mathbb{C})$ , i.e.,  $\mu$  is a complex measure on  $\mathbb{R}$ .

First we prove an auxiliary result on the convergence of products. We use the notation  $|\bullet|_+ = \max\{0, \bullet\}$ .

**Lemma 5.1.** *Let  $\mu \in M(\mathbb{R}; \mathbb{C})$  be such that  $\mu(\mathbb{R}) = 1$  and  $\int_{\mathbb{R}} (|\log|x||_+ + 1)|\mu|(dx) < \infty$ . Then the product  $\prod_{k=1}^{\infty} \hat{\mu}(\rho^{-k}\underline{\omega})$  converges uniformly on compact subsets of  $\mathbb{R}$  towards a continuous function.*

**Proof.** Since  $\mu(\mathbb{R}) = 1$  we have  $\hat{\mu}(\underline{\xi}) - 1 = \int_{\mathbb{R}} (e^{-i2\pi x \underline{\xi}} - 1)\mu(dx)$ , and hence

$$|\hat{\mu}(\underline{\xi}) - 1| \leq \int_{\mathbb{R}} 2|\sin(\pi x \underline{\xi})|\mu(dx), \quad \underline{\xi} \in \mathbb{R}.$$

Let  $m$  be a positive integer and let  $\omega \in \mathbb{R}$ . Now it is clear from the preceding inequality, Fubini's theorem, and the fact that  $|\sin(\underline{t})| \leq \min\{1, |\underline{t}|\}$  that

$$\begin{aligned} \sum_{k=m}^{\infty} |\hat{\mu}(\rho^{-k}\omega) - 1| &\leq 2 \sum_{k=m}^{\infty} \int_{\mathbb{R}} |\sin(\rho^{-k}\pi x \omega)|\mu(dx) \\ &\leq 2 \int_{\mathbb{R}} \left( \sum_{k=m}^{\lfloor \log_{\rho}(\pi|x\omega|) \rfloor} 1 + \sum_{k=\max\{\lfloor \log_{\rho}(\pi|x\omega|) \rfloor + 1, m\}}^{\infty} \rho^{-k}\pi|x\omega| \right) |\mu|(dx) \\ &\leq 2 \int_{\mathbb{R}} \left( |\lfloor \log_{\rho}(\pi|x\omega|) \rfloor + 1 - m|_+ + \frac{1}{\rho-1} \rho^{-|m - \lfloor \log_{\rho}(\pi|x\omega|) \rfloor - 1|_+} \right) |\mu|(dx). \end{aligned}$$

From this inequality we get the uniform convergence on compact intervals of the series and this implies the claim of the lemma by [1, Th. 15.4].  $\square$

We proceed with an easy result.

**Proposition 5.2.** *Assume  $\rho > 1$  and that  $\mu \in M(\mathbb{R}; \mathbb{C})$  satisfies  $|\mu(\mathbb{R})| \leq 1$  and  $\int_{\mathbb{R}} (|\log|x||_+ + 1)|\mu|(dx) < \infty$  if  $|\mu(\mathbb{R})| = 1$ . If equation (5.2) has a nontrivial solution  $f \in L^1(\mathbb{R}; \mathbb{C})$ , then  $\mu(\mathbb{R}) = 1$  and this solution is unique in  $L^1(\mathbb{R}; \mathbb{C})$  up to a multiplicative constant.*

**Proof.** Taking Fourier transforms of both sides of (5.2) we get

$$(5.3) \quad \hat{f}(\rho \underline{\omega}) = \hat{\mu}(\underline{\omega}) \hat{f}(\underline{\omega}).$$

If  $|\mu(\mathbb{R})| < 1$ , then it is clear that  $\lim_{m \rightarrow \infty} \prod_{j=1}^m |\hat{\mu}(2^{-j}\omega)| = 0$  for every  $\omega \in \mathbb{R}$ . Thus we see from (5.3) that  $\hat{f}(\omega) = 0$  for all  $\omega \in \mathbb{R}$ , so we can have no nontrivial solution  $f$ .

Suppose next that  $|\mu(\mathbb{R})| = 1$ . If  $\hat{f}(0) \neq 0$ , then we conclude from (5.3) that  $\mu(\mathbb{R}) = \hat{\mu}(0) = \hat{f}(0)/\hat{f}(0) = 1$ . If  $\hat{f}(0) = 0$  then we have

$$|\hat{f}(\omega)| = \lim_{m \rightarrow \infty} \prod_{k=1}^m |\hat{\mu}(\rho^{-k}\omega)| |\hat{f}(\rho^{-m}\omega)| = 0, \quad \omega \in \mathbb{R}.$$

because the product  $\prod_{k=1}^{\infty} |\hat{\mu}(\rho^{-k}\omega)|$  converges by Lemma 5.1. Thus we see that  $f$  is identically 0.

If now  $\mu(\mathbb{R}) = 1$ , then we have by lemma 5.1 and (5.3) that

$$\hat{f}(\omega) = \hat{f}(0) \prod_{k=1}^{\infty} \hat{\mu}(\rho^{-k}\omega), \quad \omega \in \mathbb{R},$$

and we see that  $f$  is unique up to the multiplicative constant  $\hat{f}(0)$ .  $\square$

Next we consider the case where  $\mu$  in (5.2) has compact support. First we prove an auxiliary result on how the support of  $(\mu * f)(\rho\bullet)$  is related to the supports of  $\mu$  and  $f$ .

**Lemma 5.3.** *Assume that  $\rho > 1$ ,  $\mu \in M(\mathbb{R}; \mathbb{C})$  with  $\text{supp}(\mu) \subset [M_-, M_+]$  and that  $f \in L^1(\mathbb{R}; \mathbb{C})$  with  $\text{supp}(f) \subset [F_-, F_+]$ . Then*

$$(5.4) \quad \text{supp}\left((\mu * f)(\rho\bullet)\right) \subset \left[\frac{F_- + M_-}{\rho}, \frac{F_+ + M_+}{\rho}\right].$$

**Proof.** Let  $x < (M_- + F_-)/\rho$ . Then  $\rho x - t < M_- + F_- - t \leq F_-$  if  $t \geq M_-$ . Similarly when  $x > (M_+ + F_+)/\rho$  we have  $\rho x - t > M_+ + F_+ - t \geq F_+$  if  $t \leq M_+$ . This gives the desired conclusion.  $\square$

Since the previous result says that the operator  $f \rightarrow (\mu * f)(\rho\bullet)$  forces the support closer to that of  $\mu$  it is natural to expect that if  $\mu$  has compact support and there is a solution of (5.2), then this solution has compact support as well. This turns out to be the case, at least if  $f$  is integrable.

**Proposition 5.4.** *Assume that  $\rho > 1$ ,  $\mu \in M(\mathbb{R}; \mathbb{C})$  has compact support contained in the interval  $[M_-, M_+]$  and that  $\mu(\mathbb{R}) = 1$ . If  $f \in L^1(\mathbb{R}; \mathbb{C})$  satisfies (5.2), then  $f$  has compact support contained in the interval  $[\frac{M_-}{\rho-1}, \frac{M_+}{\rho-1}]$ .*

**Proof.** Let  $f \in L^1(\mathbb{R}; \mathbb{C})$  be some nontrivial function that satisfies (5.2). If we can show that  $f$  has compact support, then it follows from repeated applications of Lemma 5.3 that the support is contained in the desired interval.

Let us for simplicity assume that  $M_- < 0$  and that  $M_+ > 0$ . Let  $m \geq 0$  be an integer and let  $f_m = f - f\chi_{[\rho^m M_-, \rho^m M_+]}$ . Moreover, we define the linear operator  $T : L^1(\mathbb{R}; \mathbb{C}) \rightarrow L^1(\mathbb{R}; \mathbb{C})$  by  $T(g) = \rho(\mu * g)(\rho\bullet)$ . If we apply Lemma 5.3  $m$  times we see that  $T^m(f - f_m)$  has support contained in the

interval  $[\frac{\rho M_-}{\rho-1}, \frac{\rho M_+}{\rho-1}]$ . On the other hand we have  $T^m(f_m) = f - T^m(f - f_m)$ , and this means that

$$(5.5) \quad f(x) = T^m(f_m)(x), \quad x \notin \left[ \frac{\rho M_-}{\rho-1}, \frac{\rho M_+}{\rho-1} \right].$$

Moreover, we easily see that

$$(5.6) \quad \widehat{T^m(f_m)}(\underline{\omega}) = \prod_{k=1}^m \hat{\mu}(\rho^{-k}\underline{\omega}) \widehat{f_m}(\rho^{-m}\underline{\omega}).$$

Let  $h$  be some infinitely many times differentiable function with support contained in  $[-1, 1]$  and let  $h_\lambda = \lambda h(\lambda \bullet)$ ,  $\lambda > 0$ . Now it follows from the inversion theorem for Fourier transforms (Theorem 2.3.(b)), (5.5) and (5.6) that

$$(5.7) \quad \int_{\mathbb{R}} h_\lambda(x-t) T^m(f_m)(t) dt = \int_{\mathbb{R}} e^{i2\pi x\omega} \widehat{h_\lambda}(\omega) \prod_{k=1}^m \hat{\mu}(\rho^{-k}\omega) \widehat{f_m}(\rho^{-m}\omega) d\omega.$$

Now we know by Lemma 5.1 that  $|\prod_{k=1}^m \hat{\mu}(\rho^{-k}\omega)|$  is bounded when  $|\omega| \leq 1$ . Then it follows for all  $m \geq 1$  and  $\omega \in \mathbb{R}$  that

$$\left| \prod_{k=1}^m \hat{\mu}(\rho^{-k}\omega) \right| \leq (\sup_{\omega \in \mathbb{R}} |\hat{\mu}(\omega)|)^{\lceil \log_2(|\omega|) \rceil} \sup_{|\xi| \leq 1} \left| \prod_{k=1}^m \hat{\mu}(\rho^{-k}\xi) \right| \leq C(|\omega| + 1)^C$$

where  $C$  is some constant. Since  $h$  is infinitely many times differentiable, it follows that

$$\int_{\mathbb{R}} |\widehat{h_\lambda}(\omega)| (|\omega| + 1)^C d\omega < \infty,$$

and therefore it follows from (5.7), the dominated convergence theorem and from the fact that  $f_m \rightarrow 0$  in  $L^1(\mathbb{R}; \mathbb{C})$  and hence  $\widehat{f_m} \rightarrow 0$  in  $L^\infty(\mathbb{R}; \mathbb{C})$  as  $m \rightarrow \infty$  that

$$\lim_{m \rightarrow \infty} \int_{\mathbb{R}} h_\lambda(x-t) T^m(f_m)(t) dt = 0, \quad x \in \mathbb{R}, \quad k \geq 1.$$

But when we let  $\lambda \rightarrow \infty$  we see from (5.5) that  $f$  must have compact support.  $\square$

### 3. Construction of wavelets with compact support

When performing calculations with the filter  $\alpha$  on some real data it is clearly advantageous to have the sequence  $\alpha$  to be real. This requirement we will make throughout this section where we want to find suitable sequences  $\alpha$  that generate multiresolutions. From Theorems 4.12 and 4.13 we see that  $\alpha$  must satisfy (4.11), (4.46), and (4.48).

We get the following characterization of the Fourier transform of filters  $\alpha$  with compact (i.e., finite) support.

**Theorem 5.5.** *Let  $\{\alpha(k)\}_{k \in \mathbb{Z}}$  be a sequence of real numbers with only finitely many nonzero terms. Then (4.11) and (4.46) hold if and only if*

$$(5.8) \quad \hat{\alpha}(\underline{\omega}) = \left( \frac{1}{2}(1 + e^{-i2\pi\underline{\omega}}) \right)^N Q(e^{-i2\pi\underline{\omega}}) e^{-i2\pi L\underline{\omega}},$$

where  $N \geq 1$ ,  $L \in \mathbb{Z}$  and  $Q$  is a polynomial with real coefficients such that

$$(5.9) \quad |Q(e^{-i2\pi\underline{\omega}})|^2 = \sum_{k=0}^{N-1} \binom{N+k-1}{k} \sin(\pi\underline{\omega})^{2k} \\ + \sin(\pi\underline{\omega})^{2N} R(\cos(2\pi\underline{\omega})),$$

where  $R$  is an odd real polynomial.

**Proof.** Suppose first that (4.11) and (4.46) hold. Since we require that  $\hat{\alpha}(0) = 1$ , it follows from (4.11) that  $\hat{\alpha}(\frac{1}{2}) = 0$ . In order to see that  $\hat{\alpha}$  can be written in the form (5.8) we argue as follows: For some integer  $L$  the function  $\underline{z}^{-L} \sum_{k \in \mathbb{Z}} \alpha(k) \underline{z}^k$  is a polynomial and this polynomial vanishes in the point  $\underline{z} = -1$ . Thus it can be written in the form  $(\frac{1}{2}(1 + \underline{z}))^N Q(\underline{z})$  where  $N \geq 1$  and  $Q$  is a real polynomial. Substituting  $e^{-i2\pi\underline{\omega}}$  for  $\underline{z}$  we get (5.8).

If  $Q(\underline{z}) = \sum_{j=0}^M q_j \underline{z}^j$ , then we have

$$|Q(e^{-i2\pi\underline{\omega}})|^2 = \sum_{k=-M}^M \tilde{q}_k e^{-i2\pi k\underline{\omega}} = \tilde{q}_0 + \sum_{k=1}^M \tilde{q}_k (e^{-i2\pi k\underline{\omega}} + e^{-i2\pi k\underline{\omega}}) \\ = \tilde{q}_0 + 2 \sum_{k=1}^M \tilde{q}_k \cos(2\pi k\underline{\omega}),$$

since  $\tilde{q}_{-k} = \tilde{q}_k$  for all  $k$  because  $\tilde{q}_k = \sum_{j=\max\{0, -k\}}^{\min\{M, M-k\}} q_j \overline{q_{j+k}}$  and the coefficients  $q_j$  in  $Q$  are real. Since every term  $\cos(2\pi k\underline{\omega})$  can be written as a polynomial in  $\cos(2\pi\underline{\omega})$  (use De Moivre's formula and  $\sin(2\pi\underline{\omega})^2 = 1 - \cos(2\pi\underline{\omega})^2$ ) or equivalently as a polynomial in  $\sin(\pi\underline{\omega})^2$  we see that there exists a polynomial  $P$  such that

$$(5.10) \quad |Q(e^{i2\pi\underline{\omega}})|^2 = P(\sin(\pi\underline{\omega})^2).$$

Since  $\sin(\pi(\underline{\omega} + \frac{1}{2}))^2 = \cos(\pi\underline{\omega})^2 = 1 - \sin(\pi\underline{\omega})^2$  and  $|\frac{1}{2}(1 + e^{i2\pi\underline{\omega}})| = \cos(\pi\underline{\omega})^2$  it follows from (4.11) that

$$(5.11) \quad (1 - \underline{z})^N P(\underline{z}) + \underline{z}^N P(1 - \underline{z}) = 1,$$

on the interval  $[0, 1]$  and therefore also on  $\mathbb{R}$ . We can write  $P$  in the form  $P(\underline{z}) = \sum_{j=0}^{N-1} p_j \underline{z}^j + \bullet^N R_0(\underline{z})$ . Inserting this expression into (5.11) we get

the following system of equations for the coefficients  $p_j$ ,

$$p_0 = 1,$$

$$p_k = \sum_{j=0}^{k-1} (-1)^{k-j-1} \binom{N}{k-j} p_j.$$

Next have to we check that the solution of this recursive system of equations is

$$p_k = \binom{N+k-1}{k}, \quad 0 \leq k \leq N-1.$$

For  $k = 0$  this is certainly the case and an induction argument works because we have

$$\begin{aligned} & \sum_{j=0}^{k-1} (-1)^{k-j+1} \binom{N}{k-j} \binom{N+j-1}{j} \\ &= \frac{N}{k!} (-1)^{k+1} \sum_{j=0}^{k-1} \binom{k}{j} (-1)^j \frac{(N+j-1)!}{(N+j-k)!} x^{N+j-k} \Big|_{x=1} \\ &= \frac{N}{k!} (-1)^{k+1} \sum_{j=0}^{k-1} \binom{k}{j} (-1)^j \frac{d^{k-1}}{dx^{k-1}} x^{N+j-1} \Big|_{x=1} \\ &= \frac{N}{k!} (-1)^{k+1} \frac{d^{k-1}}{dx^{k-1}} \left( x^{N-1} (1-x)^k - (-1)^k x^{N+k-1} \right) \Big|_{x=1} \\ &= \frac{N}{k!} \frac{d^{k-1}}{dx^{k-1}} x^{N+k-1} \Big|_{x=1} = \binom{N+k-1}{k}. \end{aligned}$$

Thus we define the polynomial  $P_N$  by

$$(5.12) \quad P_N(\underline{z}) = \sum_{k=0}^{N-1} \binom{N+k-1}{k} x^k.$$

Next we observe that this polynomial is in fact a solution of (5.11), because the construction of the coefficients  $p_k$  guarantees that

$$(5.13) \quad (1 - \underline{z})^N P_N(\underline{z}) + \underline{z}^N P_N(1 - \underline{z}) - 1 = \underline{z}^N V(1 - \underline{z}),$$

where  $V$  is polynomial of at most degree  $N-1$ . But then it follows that

$$(5.14) \quad \underline{z}^N V(1 - \underline{z}) = (1 - \underline{z})^N V(\underline{z}).$$

It follows from a calculation similar to the one used for finding the coefficients  $p_k$ , that  $V$  is identically zero since it is of a most degree  $N-1$ .

The original polynomial  $P$  was written in the form  $P = P_N(\underline{z}) + \underline{z}^N R_0(\underline{z})$ . If we insert this expression in (5.11) we conclude that

$$(5.15) \quad (1 - \underline{z})^N \underline{z}^N R_0(\underline{z}) + (1 - \underline{z})^N \underline{z}^N R_0(1 - \underline{z}) = 0,$$

that is  $R_0(\underline{z}) = -R_0(1 - \underline{z})$  and this implies that  $R_0(\underline{z}) = R(1 - 2\underline{z})$  where  $R$  is an odd polynomial. But this is exactly what we wanted to prove.

The converse goes in exactly the same way.  $\square$

If we want to construct a filter sequence  $\alpha$ , one possibility is to use Theorem 5.5. But then we must be able to find the trigonometric polynomial  $Q(e^{-i2\pi\omega})$  if  $|Q(e^{-i2\pi\omega})|^2$  is known. This classical result is given in the next lemma.

**Lemma 5.6.** *Assume that  $A(\omega) = \sum_{k=-M}^M a_k e^{-i2\pi k\omega}$ , where  $a_k = a_{-k} \in \mathbb{R}$  for  $k = 0, 1, \dots, M$ , is nonnegative and  $a_M \neq 0$ . Then the  $2M$  zeros of the polynomial  $\sum_{k=-M}^M a_k \omega^{k+M}$  are of the form  $w_j, \overline{w_j}, w_j^{-1}, \overline{w_j}^{-1} \in \mathbb{C} \setminus \mathbb{R}$ , for  $j = 1, \dots, J$ , and  $r_k, r_k^{-1} \in \mathbb{R}$ , for  $k = 1, \dots, K$ , and*

$$B(\omega) = \sqrt{|a_M| \prod_{k=1}^K |r_k|^{-1} \prod_{j=1}^J |w_j|^{-2} \times \prod_{k=1}^K (e^{-i2\pi\omega} - r_k) \prod_{j=1}^J (e^{-i4\pi\omega} - 2e^{-i2\pi\omega} \operatorname{Re}(w_j) + |w_j|^2)},$$

is a trigonometric polynomial with real coefficients such that  $|B(\omega)|^2 = A(\omega)$ .

**Proof.** Let  $P_A(\underline{z}) = \sum_{k=-M}^M a_k \underline{z}^{k+M}$ . This polynomial has  $2M$  zeros (counting multiplicities) and since the coefficients are real we have  $\overline{P_A(z)} = P_A(\overline{z})$  for all  $z$ , so that if  $z$  is a zero, then  $\overline{z}$  is a zero as well. Moreover, since  $a_k = a_{-k}$  for  $k = 1, \dots, M$ , it follows that  $P_A(\underline{z}) = \underline{z}^{2M} P_A(\frac{1}{\underline{z}})$  and this implies that if  $z$  is a zero of  $P_A$ , then so is  $z^{-1}$ . (The assumption  $a_M \neq 0$  guarantees that  $P_A(0) \neq 0$ .) Moreover, every zero on the unit circle has even multiplicity because  $z^{-M} P_A(z)$  is by assumption nonnegative on the unit circle. 1 is a zero, then we see from the relation  $P_A(\underline{z}) = \underline{z}^{2M} P_A(\frac{1}{\underline{z}})$  that it is actually a zero of even multiplicity. This gives the conclusion about the zeros of  $P_A$ .

Thus we can write  $P_A$  in the form

$$P_A(\underline{z}) = a_M \left( \prod_{k=1}^K (\underline{z} - r_k)(\underline{z} - r_k^{-1}) \right) \times \left( \prod_{j=1}^J (\underline{z} - w_j)(\underline{z} - \overline{w_j})(\underline{z} - w_j^{-1})(\underline{z} - \overline{w_j}^{-1}) \right).$$

Since we for every  $z \in \mathbb{C} \setminus 0$  have

$$\begin{aligned} |(e^{-i2\pi\underline{\omega}} - z)(e^{-i2\pi\underline{\omega}} - \bar{z}^{-1})| &= |z|^{-1} |(e^{-i2\pi\underline{\omega}} - z)(\bar{z} - e^{i2\pi\underline{\omega}})| \\ &= |z|^{-1} |e^{-i2\pi\underline{\omega}} - z|^2, \end{aligned}$$

it follows from the nonnegativity of  $A$  and the fact that  $|A(\underline{\omega})| = |P_A(e^{-i2\pi\underline{\omega}})|$  that

$$\begin{aligned} A(\underline{\omega}) &= |A(\underline{\omega})| = |P_A(e^{-i2\pi\underline{\omega}})| = |a_M| \prod_{k=1}^K |r_k|^{-1} \prod_{j=1}^J |w_j|^{-2} \\ &\times \left| \prod_{k=1}^K (e^{-i2\pi\underline{\omega}} - r_k) \prod_{j=1}^J (e^{-i2\pi\underline{\omega}} - w_j)(e^{-i2\pi\underline{\omega}} - \bar{w}_j) \right|^2 = |B(\underline{\omega})|^2. \end{aligned}$$

This completes the proof.  $\square$

If we want to construct a wavelet with compact support, the simplest approach according to Theorem 5.5 is to choose a positive integer  $N$ , take  $L = 0$  for simplicity, since another choice only amounts to a translation, choose the polynomial in (5.9) to be identically zero, and so on.

We leave it as an exercise to show that in this way we get a filter that in addition to (4.11) and (4.46) also satisfies (4.48) and therefore generates a father wavelet or scaling function that turns out to be continuous if  $N > 1$ . In fact one can say much more about the smoothness of these functions but this question will not be studied here.

#### 4. Properties of compactly supported wavelets

First we consider briefly the question of how one can efficiently calculate the values of the function  $\varphi$ .

**Proposition 5.7.** *Assume that  $(\alpha(k))_{k \in \mathbb{Z}}$  is such that  $\alpha(k) = 0$  when  $k \leq a_-$  or  $k > a_+$ ,  $\sum_{k=a_-}^{a_+} \alpha(k) = 1$  and  $\varphi \in \mathcal{C}_c(\mathbb{R})$ , with  $\varphi \not\equiv 0$ , is a solution to the equation*

$$\varphi(\underline{x}) = 2 \sum_{k \in \mathbb{Z}} \alpha(k) \varphi(2\underline{x} - k).$$

*Then the matrix  $A$  defined by  $A(i, j) = 2\alpha(2i - j)$ ,  $i, j = a_- + 1, \dots, a_+ + 1$  has the eigenvalue 1,  $(\varphi(a_- + 1), \dots, \varphi(a_+ + 1))^T$  is an eigenvector for this eigenvalue and the values of  $\varphi$  at the points  $2^{-j}n$ ,  $j \geq 1$  can be recursively calculated from the equation*

$$\varphi(2^{-j}n) = 2 \sum_{k=a_-}^{a_+} \alpha(k) \varphi(2^{-j+1}n - k), \quad n \in \mathbb{Z}, \quad j \geq 1.$$



Observe that we do not claim that the eigenvalue 1 from the matrix  $A$  has geometric multiplicity 1 so it is may not be clear which eigenvector to choose, but in most cases this turns out not to be the case.

Our next result restricts the smoothness of the scaling function  $\varphi$  in terms of the support of the filter  $\alpha$ .

**Theorem 5.8.** *If  $m \geq 0$  and  $f \in C^m(\mathbb{R}; \mathbb{C})$ ,  $f \not\equiv 0$ , has compact support and satisfies*

$$(5.16) \quad f = 2 \sum_{k=a_-}^{a_+} \alpha(k) f(2 \bullet - k),$$

for some numbers  $\{\alpha(k)\}$ , then  $m < a_+ - a_- - 1$ .

**Proof.** If we apply Lemma 5.3, we see that the support of  $f$  must be contained in the closed interval  $[a_-, a_+]$ . Thus the support of  $f^{(j)}$  must also be contained in this interval for  $0 \leq j \leq m$ . Moreover, differentiating both sides of (5.16) we get

$$(5.17) \quad f^{(j)} = 2^{j+1} \sum_{k=a_-}^{a_+} \alpha(k) f^{(j)}(2 \bullet - k).$$

Let  $A$  be a matrix with elements  $A(i, j) = 2\alpha_{2i-j}$  for  $i, j = a_- + 1, \dots, a_+ - 1$  (the indexing is nonstandard but this is of no consequence). Now we see from (5.17) that if the vector  $(f^{(j)}(a_- + 1), f^{(j)}(a_- + 2), \dots, f^{(j)}(a_+ - 1))^T$  is not the zero vector, then it is an eigenvector of the matrix  $A$  corresponding to the eigenvalue  $2^{-j}$ . We leave it as an exercise to show that this vector cannot be the zero vector. Thus  $A$  has at least  $m + 1$  distinct eigenvalues so that  $A$  must be at least an  $(m + 1) \times (m + 1)$  matrix. Thus we see that  $m + 1 \leq a_+ - a_- - 1$  and this gives the desired conclusion.  $\square$

Next we show that except for the Haar function, no father wavelet or scaling function for a multiresolution can not be symmetric with respect to any point.

**Proposition 5.9.** *Let  $(\{V_m\}_{m \in \mathbb{Z}}, \varphi)$  be a multiresolution of  $L^2(\mathbb{R}; \mathbb{C})$  such that  $\varphi$  is real-valued and has compact support. Then  $\varphi$  is not symmetric (nor antisymmetric) with respect to any point unless  $\varphi$  is the Haar function  $\chi_{[0,1]}$ .*

**Proof.** It is clear that we cannot have  $\varphi(\lambda + \bullet) = -\varphi(\lambda - \bullet)$  for some  $\lambda \in \mathbb{R}$ , because then we would have  $\int_{\mathbb{R}} \varphi(x) dx = 0$  which is impossible by Theorem 4.9.

Suppose on the other hand that  $\varphi(\lambda + \bullet) = \varphi(\lambda - \bullet)$ . If  $\lambda$  is an integer, then can take an integer translation of  $\varphi$ , so we may without loss of generality

assume that  $\varphi$  is an even function. It follows that the filter  $\alpha$  is even as well and has compact support. We shall show that this leads to a contradiction.

Let us introduce the notation that if  $p$  is a trigonometric polynomial with period 1, i.e.,  $p = \sum_k \hat{p}(k)e^{i2\pi k\bullet}$ , then

$$\begin{aligned} N_+(p) &= \max\{k \mid \hat{p}(k) \neq 0\}, \\ N_-(p) &= \min\{k \mid \hat{p}(k) \neq 0\}. \end{aligned}$$

It is easy to check that

$$(5.18) \quad N_+(|p|^2) = -N_-(|p|^2) = N_+(p) - N_-(p).$$

Let  $\alpha^e$  be the sequence  $\alpha_k^e = \frac{1}{2}(1 + (-1)^k)\alpha(k)$  with nonzero even indices and  $\alpha^o$  the sequence  $\alpha_k^o = \frac{1}{2}(1 - (-1)^k)\alpha(k)$  with nonzero odd indices. Since  $\widehat{\alpha^e} = \frac{1}{2}(\hat{\alpha}(\bullet) + \hat{\alpha}(\bullet + \frac{1}{2}))$  and  $\widehat{\alpha^o} = \frac{1}{2}(\hat{\alpha}(\bullet) - \hat{\alpha}(\bullet + \frac{1}{2}))$ , it follows from (4.11) that

$$(5.19) \quad |\widehat{\alpha^e}|^2 + |\widehat{\alpha^o}|^2 = \frac{1}{2}.$$

Since neither  $\alpha^e$  nor  $\alpha^o$  can be identically zero (because  $\widehat{\alpha^e}(0) = \widehat{\alpha^o}(0) = \frac{1}{2}$ ) it follows from (5.18) that

$$(5.20) \quad N_+(\widehat{\alpha^e}) - N_+(\widehat{\alpha^o}) = N_+(\widehat{\alpha}) - N_+(\widehat{\alpha^e}).$$

From the definition of  $\alpha^e$  and  $\alpha^o$  we get

$$\begin{aligned} N_+(\hat{\alpha}) &= \max\{N_+(\widehat{\alpha^e}), N_+(\widehat{\alpha^o})\}, \\ N_-(\hat{\alpha}) &= \min\{N_-(\widehat{\alpha^e}), N_-(\widehat{\alpha^o})\}, \end{aligned}$$

If we combine this result with (5.20) we conclude that

$$(5.21) \quad N_+(\hat{\alpha}) - N_-(\hat{\alpha}) = \max\{N_+(\widehat{\alpha^e}) - N_-(\widehat{\alpha^o}), N_+(\widehat{\alpha^o}) - N_-(\widehat{\alpha^e})\}.$$

Since  $N_\pm(\widehat{\alpha^e})$  are even numbers and  $N_\pm(\widehat{\alpha^o})$  are odd numbers, it follows that  $N_+(\hat{\alpha}) - N_-(\hat{\alpha})$  is an odd number. But then  $\alpha$  cannot be an even sequence and we have a contradiction.

Assume next that  $\varphi(\lambda + \bullet) = \varphi(\lambda - \bullet)$  where  $\lambda$  is not an integer. We may again shift the function  $\varphi$  so that  $\lambda \in (0, 1)$ . Taking Fourier transforms we get

$$(5.22) \quad \hat{\varphi}(\bullet) = e^{-4\pi i \lambda \bullet} \hat{\varphi}(-\bullet).$$

But then it follows from (4.10) that we also have

$$(5.23) \quad \hat{\alpha}(\bullet) = e^{-4\pi i \lambda \bullet} \hat{\alpha}(-\bullet).$$

Now  $\hat{\alpha}$  and  $\hat{\alpha}(-\bullet)$  are both trigonometric polynomials with period 1 and therefore we must have  $\lambda = \frac{1}{2}$ . Thus we have  $\varphi(\bullet + 1) = \varphi(-\bullet)$ . It follows

from (4.8) after some changes of variables that  $\alpha_{2k+1} = \alpha_{-2k}$  for all  $k \in \mathbb{Z}$ . Since  $\varphi$  is real-valued,  $\alpha$  is real-valued as well, and hence we have

$$(5.24) \quad \widehat{\alpha^e} = \overline{\widehat{\alpha^o}},$$

and combining this result with (5.19) we get

$$(5.25) \quad |\widehat{\alpha^e}|^2 = \frac{1}{4}.$$

It follows that there exists an index  $k$  such that  $\alpha_j = \frac{1}{2}$  when  $j = 2k + 1$  or  $j = -2k$ . If  $k = 0$ , then we get the Haar function and otherwise we get

$$(5.26) \quad \hat{\alpha} = e^{-\pi i \bullet} \cos((4k + 1)\pi \bullet).$$

But then it follows from Proposition 4.15 that (4.48) cannot hold true, and this contradicts Theorem 4.13.  $\square$